Ampheia™

Ultra-Low Noise | Single frequency | Fiber Amplifier




Applications

Atom Trapping
Particle Analysis
Optical Metrology
Laser Interferometry
Frequency Conversion
Quantum Sensing


Features

a perfect beam.

- Up to 50 W, CW, single-frequency emission
- Ultra-low noise and perfect beam quality
- Single-stage fiber amplifier with integrated seed laser
- Signal to noise ratio (OSNR> 60 dB)
- Robust and maintenance free
- Easy installation and user-friendly interface



Typical Optical Signal to Noise Ratio (OSNR)



Ampheia[™] is a single-stage fiber amplifer built around an internal seed laser and presents affordable, outstanding laser performance tailored for quantum applications. Offered in a 19 inch 3U rack case, this amplifier offers excellent robustness.


The Ampheia™ Series is a family of high-power fiber amplifiers,

which with a pinnacle of perfection seamlessly boosting

ultra-low relative intensity noise (RIN) and single-frequency operation while delivering 20 W, 40 W, and 50 W at 1064 nm in

With single-frequency precision, the fiber amplfier offers a long coherence length. Thoroughly designed and manufactured, Ampheia™ Series of fiber amplifiers guarantee a high level of reliability, making them ideal for stand-alone use or seamless integration as an OEM component. It caters to a spectrum of applications ranging from atomic trapping, optical metrology, laser interferometry, frequency conversion to quantum sensing.

Typical TEMoo Beam







Ampheia™

Optical Specifications


	Ampheia™		
Wavelength	1064.2 ±0.6 nm		
Output power after integrated isolator	20 W	40 W	50 W
Operation mode	Continuous wave		
Spectral linewdth (FWHM)	< 30 kHz		
Coherence length	> 1 km		
Polarization extincion ratio (PER) (Vertiacally polarized)	> 30 dB		
Beam quality (M²)	< 1.1	< 1.15	< 1.2
Spatial mode	TEMoo		
Nominal beam diameter at 1/e²	1± 0.1 mm		
Noise [100 Hz- 10 MHz]	< 0.05 % RMS		
Relative intensity noise (RIN) [10 kHz- 1 MHz]	< - 145 dB/Hz		
Optical signal to noise ratio (OSNR)	> 6o dB		
Output power tunability	5 to 100 %		
Fiber delivery cable length	2 M	1.2 M	1.0 m

Electrical/Meachanical/Operational Environmental Specifications

Fiber amplifier rack weight	14.3 kg (31.5 lbs.)	
Fiber amplifier rack dimensions (LxWxH)	470.5x423x133 mm (18.52x16.65x5.24 in.)	
Laser head weight	o.56 kg (1.23 lbs.)	
Laser head dimensions (LxWxH)	155x55x45 mm (6.10x2.17x0.87 in.)	
Intended use environment	Laboratory (indoor)	
Ambient temperature, operation	18 - 30 °C (Air-cooled)	
Ambient temperature, storage	-10 to +60 °C	
Humidity	o - 6o % RH non-condensing	
Laser head heat sink thermal impedance (at 30°C ambient)	< 2 K/W	
System power consumption	< 300 W	
Maximum heat dissipation of laser Head	< 2 W¹	

^{1.} With emergency shutter 50W closed, under less than 6os.

Model Number



Communication Interface

Communication	USB or RS-232
Standard Baudrate	115200



WARNING VISIBLE OR INVISIBLE LASER RADIATION Avoid Exposure to beam Class 4 Laser Product Classified per IEC 60825-1:2014



Wvl (nm) Max.Pwr (W) 1064 50





This device is sensitive to Elecrostatic Discharge (ESD).

Ampheia™


Mechanical Specifications


Fiber Amplifier Rack dimensions





Laser head dimensions







Our Locations

Cobolt AB a part of HÜBNER Photonics (Sales in Norway, Sweden, Finland and Denmark)

Solna, Sweden

Phone: +46 8 545 912 30 Fax: +46 8 545 912 31

E-mail: info.se@hubner-photonics.com

HÜBNER GmbH & Co. KG (Sales in Germany, Switzerland and Austria)

Kassel, Germany

Phone: +49 561 994 060 - 0 Fax: +49 561 994 060 - 13

E-mail: info.de@hubner-photonics.com

HÜBNER Photonics Inc. (Sales in USA, Canada and Mexico)

San Jose, California, USA

Phone: +1 (408) 708 4351 Fax: +1 (408) 490 2774

E-mail: info.usa@hubner-photonics.com

HA Photonics Pty Ltd (Agent) (Sales in UK & Ireland - goods shipped from Europe)

Derby, Great Britain Phone: +44 735 944 0871

E-mail: info.uk@hubner-photonics.com

Find local sales representatives at <u>hubner-photonics.com</u>